

# CoaCh400

## Personal Wireless Portable Amplifier

### General Features

- High efficiency output power with inbuilt 25W class-D power amplifier.
- Truly wireless! Battery operation eliminates all cables so you can take it anywhere.
- 4" full range speaker system with maximum output of 40W
- USB 2.0 port for reading MP3 files with LCD display of track information
- Band selection of wireless microphone system : UHF (16 CH. switchable) or UHF/ VHF (fixed frequency)
- Input : Wired microphone, Aux In, USB 2.0
- Output : Aux Out
- 2 alarm sounds for emergency broadcasting
- Lithium battery offers extended operation time and minimizes the weight and size
- $\Phi$  3.5mm stereo Aux In/Aux Out connectors
- Can be worn over the shoulder or mounted on ST-30 tripod stand.
- Suitable for outdoor/indoor applications such as lectures, trade fairs, tours and election events etc



### Specifications

Model	Coach 400
Output Power	Max 40W /25W(RMS) 4 $\Omega$ load
Speaker System	4" full range
T.H.D.	< 0.5%
Audio Inputs	Mic in 、 Aux in 、 USB2.0
Audio Outputs	Aux out
Power Supply	1001240V 1.5A , 20VDC 2.5A
Battery Type	14.8V / 2.4AH (Lithium)
Operating Life	5-6 hours in music, 10-12 hours in speech about 4 hours
Charging Time	156H, 156W, 205D
Dimension (mm)	1.6
Weight (kg)	Taiwan, China
Approval	CE 、 RoHS
Module type	R-300m, R-500m, SDR-500m
Frequency Response	50Hz-20KHz $\pm$ 3dB
Antenna	Built-in



Wireless Portable Amplifiers